



Ref. Certif. No.

SE-113563

IEC SYSTEM FOR MUTUAL RECOGNITION OF TEST CERTIFICATES FOR ELECTRICAL EQUIPMENT (IECEE) CB SCHEME

CB TEST CERTIFICATE

Product

Motor starter

Name and address of the applicant

Zhejiang Chint Electrics Co., Ltd.
No.1 Chint Road, Chint Industrial Zone, North Baixiang,
Yueqing, Zhejiang Province, P.R.China

Name and address of the manufacturer

Same as applicant

Name and address of the factory

Same as applicant

Note: When more than one factory, please report on page 2

Additional Information on page 2

Ratings and principal characteristics

Ue=400/415V, 690V~, 3P, 50/60Hz,
Ui=690V, Uimp=8kV, Cat. A, AC-3,
In=0,16, 0,25, 0,4, 0,63, 1, 1,6, 2,5, 4, 6,3, 10, 14, 18, 23,
25, 32A,

Trademark / Brand (if any)

CHNT

Customer's Testing Facility (CTF) Stage used

-

Model / Type Ref.

NS2-***

Additional information (if necessary may also be reported on page 2)

Additional Information on page 2

A sample of the product was tested and found to be in conformity with

IEC 60947-1:2007+A1+A2
IEC 60947-2:2016+A1
IEC 60947-4-1:2018

As shown in the Test Report Ref. No. which forms part of this Certificate

2401B0963SHA-001, -002

This CB Test Certificate is issued by the National Certification Body

Intertek Semko AB
Torshamnsgatan 43
Box 1103
SE-164 22 Kista, Sweden

Date: 13 March, 2024

intertek

Signature:

Anneli Averland Johansson

Additional information

Rated Current (A)	Adjustable current settings (A)	Ii (A)	Short-circuit capacity			
			400V/415V~		690V~	
			Icu (kA)	Ics (kA)	Icu (kA)	Ics (kA)
0,16	0,1-0,16	1,5	100	100	100	100
0,25	0,16-0,25	2,4	100	100	100	100
0,4	0,25-0,4	5	100	100	100	100
0,63	0,4-0,63	8	100	100	100	100
1	0,63-1	13	100	100	100	100
1,6	1-1,6	22,5	100	100	100	100
2,5	1,6-2,5	33,5	100	100	3	2,25
4	2,5-4	51	100	100	3	2,25
6,3	4-6,3	78	100	100	3	2,25
10	6-10	138	100	100	3	2,25
14	9-14	170	15	7,5	3	2,25
18	13-18	223	15	7,5	3	2,25
23	17-23	327	15	6	3	2,25
25	20-25	327	15	6	3	2,25
32	24-32	416	10	5	3	2,25

Explanation for the mode / type:

N S 2 - * * *
 I II III IV V VI

I. Enterprise code

II. Motor starter

III. Design code

IV. Frame size: 25 : 25A, 32 : 32A

V. Blank: button, X: rotatory handle

VI. Blank: conventional type, XM: high protection type

Date: 13 March, 2024

Signature:

